


# iGVD71 BX-CAT DATASHEET

P/N: P025.027.E221



All dimensions are in mm; Drawing not to scale.

## Motor – sensor configurations

Motor	PMSM	BLDC	DC BRUSH
Incr. Encoder	Ⓣ		Ⓣ
Incr. Encoder + Dig. Hall	Ⓣ	Ⓣ	
Digital Hall control only	Ⓣ		
Analog Sin/Cos encoder	Ⓣ	Ⓣ	Ⓣ
SSI / BiSS-C / EnDAT / Tamagawa / Panasonic / Nikon / Sanyo Denki	Ⓣ	Ⓣ	Ⓣ
Tacho			Ⓣ

### Features

- Motion controller and drive in a single compact unit based on MotionChip™ technology
- Universal solution for control of rotary and linear brushless and brushed motors
- Advanced motion control capabilities (PVT, S-curve, electronic cam)
- Motor supply: 11-80V; Logic supply<sup>1</sup>: 9-36V
- Output current<sup>2</sup>:
  - Nominal: 71 A<sub>RMS</sub> / 100A amplitude
  - Peak: 92 A<sub>RMS</sub> / 130A amplitude
- <sup>3</sup>STO: 2 safe torque-off inputs, 18-36V SELV/PELV supply, safety integrity level (SIL3) acc. to EN61800-5-1; -2/ EN61508-3; -4/ EN ISO 13849-1.
- 5x opto-isolated digital inputs, 12-36V, PNP/NPN compatible: 2 for limit switches, 3 general-purpose
- 4x digital outputs, 0.2A PNP/ 0.3A NPN software selectable: Ready, Error, 2 general-purpose
- 1x PNP/NPN 2A Solenoid driver for motor brake: Out0/Brake
- 2x analogue inputs: 12 bit, 0-5V: Reference and Feedback (for Tacho) or general-purpose
- Feedback Devices (dual-loop support)
  - 1<sup>st</sup> feedback devices supported:
    - Incremental encoder interface (single-ended or differential)
    - Analogue sin/cos encoder interface (differential 1Vpp)
  - 2<sup>nd</sup> feedback devices supported:
    - Incremental encoder interface (single-ended or differential)

- BISS / SSI / EnDAT / TAMAGAWA / Panasonic/ Nikon/ Sanyo Denki encoder interface
- Digital Hall sensor interface (single-ended / open collector or differential, selectable by DIP switch)
- Pulse & direction reference (single-ended or differential) capability
- <sup>4</sup>USB & dual 100Mbps RJ45 EtherCAT® interfaces
- Commissioning (set-up) possible through USB, FoE (file-over-EtherCAT®), EoE (Ethernet-over-EtherCAT®)
- 32 h/w addresses selectable by DIP switch
- 16k x 16 SRAM memory for data acquisition
- 16k x 24 E<sup>2</sup>ROM to store setup data, TML motion programs, cam tables and other user data
- Operating ambient temperature: 0-40°C (over 40°C with derating)

<sup>1</sup> Logic supply must be SELV/ PELV type (Safety Extra Low Voltage / Protective Extra Low Voltage)

<sup>2</sup> Nominal output current possible only with external radiator (not included) that can maintain lower plate temperature below 75°C; The radiator is mounted under the drive using thermal paste or direct metal contact. Its size is application dependent

<sup>3</sup> The STO circuit must be supplied with minimum 18V to enable PWM output

<sup>4</sup> Micro USB cable not provided

### Mating Connectors

Ref	Component	Function
J1	High AMP wire. 4mm HEX socket. AWG 6-16 wire gauge.	Motor Phases
	Strip: <ul style="list-style-type: none"> <li>- min 8 mm for cables with isolation diameter less than .5 mm;</li> <li>- min 12 mm/ max 15 mm for cables with isolation diameter bigger than 6.5 mm.</li> </ul>	Motor Supply
	<b>Avoid generating metal debris/ filings into drive from the wire leads! In case of multi-stranded wires, a proper crimp ferrule* must be used as wire terminal.</b>	
J2, J3	generic 15-pin High Density D-Sub male	Feedback #1 Halls Feedback #2
J4	generic 15-pin High Density D-Sub female	I/O's
J5	Female connector; CAGE CLAMP®; 0.5 mm <sup>2</sup> ; Pin spacing 2.5 mm; 6-pole	STO Logic Supply
J6	Standard Micro USB cable	Communication
J7, J8	Standard 8P8C modular jack (RJ-45) male	EtherCAT

\* For more recommendations about wires and ferrules, check the User Manual of the drive.

Name ALN	First edition January 20, 2023	Document template: P099.TQT.564.0001	Last edition October 10, 2025	Visa: AS, GC
		Title of document <b>iGVD71 BX-CAT Intelligent Drive PRODUCT DATA SHEET</b>	N° document <b>P025.027.E221.DSH.011</b>	
				Page: 1 of 4

# iGVD71 BX-CAT DATASHEET

## P/N: P025.027.E221

Pin	Name	Description
1	GND	Negative return (ground) of the power supply
2	C	Phase C for 3-ph motors
3	B	Phase B for 3-ph motors, Motor- for DC brush motors
4	A	Phase A for 3-ph motors, Motor+ for DC brush motors
5	+VMOT	Positive terminal of the motor supply: 11 to 80V <sub>DC</sub> .

Pin	Name	Description
1	+5V <sub>OUT</sub>	5V output supply
2	Data+/ SL+	Data+ for SSI & EnDAT, or Slave+ for BiSS C; SW1 pin 9 can connect an 120Ω resistor between pins 2 and 3
3	Data-/ SL-	Data- for SSI & EnDAT, or Slave- for BiSS C; SW1 pin 9 can connect an 120Ω resistor between pins 2 and 3
4	B2+/ Dir+	Incr. encoder2 B+ diff. input, or Dir+; SW1 pin 9 can connect an 120Ω resistor between pins 4 and 14
5	A2+/ Pulse+	Incr. encoder2 A+ diff. input, or Pulse+; SW1 pin 9 can connect an 120Ω resistor between pins 4 and 14
6	+V <sub>LOG</sub>	Positive terminal of the logic supply: 9 to 36V <sub>DC</sub> . Internally connected to other +V <sub>LOG</sub> pins.
7	CLK+/ MA+	Clock+ for SSI & EnDAT or Master+ for BiSS C; SW1 pin 9 can connect an 120Ω resistor between pins 7 and 8
8	CLK-/ MA-	Clock- for SSI & EnDAT or Master- for BiSS C; SW1 pin 9 can connect an 120Ω resistor between pins 7 and 8
9	Z2+	Incr. encoder2 Z single-ended input, Z2+ diff. input; SW1 pin 9 can connect an 120Ω resistor between pins 9 and 10
10	Z2-	Incr. encoder2 Z- diff. input; SW1 pin 9 can connect an 120Ω resistor between pins 9 and 10
11	GND	Return ground for sensors supply
12	FDBK	Analogue input, 12-bit, 0-5V
13	Rsvd.	Reserved. Do not connect
14	B2-/ Dir-	Incr. encoder2 B- diff. input, or Dir-; SW1 pin 9 can connect an 120Ω resistor between pins 4 and 14
15	A2-/ Pulse-	Incr. encoder2 A- diff. input, or Pulse-; SW1 pin 9 can connect an 120Ω resistor between pins 5 and 15

Pin	Name	Description
1	+V <sub>LOG</sub>	Positive terminal of the logic supply input: 9 to 36V <sub>DC</sub> from SELV/ PELV type power supply.
2	-V <sub>LOG</sub>	Negative terminal of the logic supply input: 9 to 36V <sub>DC</sub> from SELV/ PELV type power supply.
3	STO2-	Safe Torque Off input 2, negative return (opto-isolated, 18+36V)
4	STO2+	Safe Torque Off input 2, positive input (opto-isolated, 18+36V)
5	STO1-	Safe Torque Off input 1, negative return (opto-isolated, 18+36V)
6	STO1+	Safe Torque Off input 1, positive input (opto-isolated, 18+36V)

Apply between both STO1+, STO2+ and STO1-, STO2- minimum 18V DC from SELV/ PELV power supply for motor PWM output operation

Pin	Name	Position	Description
1	ID-Bit0	up (ON)	Hardware AxisID selection switches All switches ON – AxisID= 31 All switches OFF – AxisID= 255 When Axis ID is 255, the EtherCAT register called "configured station alias" will be 0.
2	ID-Bit1	up (ON)	
3	ID-Bit2	up (ON)	
4	ID-Bit3	up (ON)	
5	ID-Bit4	up (ON)	
6	Rsvd.	-	Reserved
7	Hall 120Ω	up (ON)	Internally connects 120Ω termination resistors between Hall signals
8	Fdbk #1 120Ω	up (ON)	Internally connects 120Ω termination resistors between Feedback #1 signals
9	Fdbk #2 120Ω	up (ON)	Internally connects 120Ω termination resistors between Feedback #2 signals

LEDS	TML Error	RED	Turned on when the drive detects an error condition
	TML Ready	GREEN	Lit after power-on when the drive initialization ends. Turned off when an error occurs.
	ECAT Error	RED	EtherCAT® ERROR and RUN indicators shows the state of the EtherCAT® Status Machine
	ECAT Run	GREEN	

Pin	Name	Description
1	+5V <sub>OUT</sub>	5V output supply
2	Hall 1+	Digital input Hall 1 sensor input or Hall1+ diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 2 and 6
3	Hall 2+	Digital input Hall 2 sensor input or Hall2+ diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 3 and 7
4	B1+/ Cos+	Incr. encoder1 B single-ended input, B1+ diff. input or analogue encoder Cos+ diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 4 and 14
5	A1+/Sin+	Incr. encoder1 A single-ended input, A+ diff. input, or analogue encoder Sin+ diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 5 and 15
6	Hall 1-	Digital input Hall 1- diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 2 and 6
7	Hall 2-	Digital input Hall 2- diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 3 and 7
8	Hall 3-	Digital input Hall 3- diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 13 and 8
9	Z1+	Incr. encoder1 Z single-ended input or Z+ diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 9 and 10
10	Z1-	Incr. encoder1 Z- diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 9 and 10
11	GND	Return ground for sensors supply
12	Temp Mot	Analogue input, 12-bit, 0-3.3V. Used to read an analog temperature value
13	Hall 3+	Digital input Hall 3 sensor input or Hall3+ diff. sensor input; SW1 pin 7 can connect an 120Ω resistor between pins 13 and 8
14	B1-/Cos-	Incr. encoder1 B- diff. input, or analogue encoder Cos- diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 4 and 14
15	A1-/Sin-	Incr. encoder1 A- diff. input, or analogue encoder Sin- diff. input; SW1 pin 8 can connect an 120Ω resistor between pins 5 and 15

Pin	Name	Description
1	IN0	12-36V general-purpose digital PNP/NPN opto-isolated input.
2	IN4	12-36V general-purpose digital PNP/NPN opto-isolated input.
3	IN2/LSP	12-36V digital PNP/NPN opto-isolated input. Positive limit switch function
4	REF	Analogue input, 12-bit, 0-5V
5	Earth	Earth connection; Internally connected to the metallic side of J2, J3 and J4
6	+V <sub>LOG</sub>	Positive terminal of the logic supply: 9 to 36V <sub>DC</sub> . Internally connected to other +V <sub>LOG</sub> pins.
7	IN1	12-36V general-purpose digital PNP/NPN opto-isolated input.
8	IN3/LSN	12-36V digital PNP/NPN opto-isolated input. Negative limit switch function
9	GND PNP +Vlog NPN	PNP/NPN Inputs type selector. Connect to GND to use inputs as PNP; Connect to +Vlog to use inputs as NPN
10	GND	Return ground for I/O pins
11	OUT0/Brake	Digital output used for an electro-mechanical brake, 12-36V, 2A PNP/ 2A NPN software selectable
12	OUT1	12-36V general-purpose digital output, 0.2A PNP/ 0.3A NPN, software selectable
13	OUT4	12-36V general-purpose digital output, 0.2A PNP/ 0.3A NPN, software selectable
14	OUT2/Error	12-36V drive Error digital output, 0.2A PNP/ 0.3A NPN, software selectable
15	OUT3/Ready	12-36V drive Ready digital output, 0.2A PNP/ 0.3A NPN, software selectable

**J6 USB** Standard micro-USB port. Is identified in Windows as RS-232 COM port

Name ALN	First edition January 20, 2023	Document template: P099.TQT.564.0001	Last edition October 10, 2025	Visa: AS, GC
 <b>TECHNOSOFT</b>		<b>iGVD71 BX-CAT</b> <b>Intelligent Drive</b> <b>PRODUCT DATA SHEET</b>		<b>P025.027.E221.DSH.011</b>
		Page: 2 of 4		

# iGVD71 BX-CAT DATASHEET

P/N: P025.027.E221

## Electrical characteristics

All parameters measured under the following conditions (unless otherwise specified):

- $V_{LOG} = 24 \text{ VDC}$ ;  $V_{MOT} = 80 \text{ VDC}$ ;  $F_{PWM} = 20 \text{ kHz}$
- Supplies start-up / shutdown sequence: -any-
- Load current (sinusoidal amplitude) = 100A

Operating Conditions		Min.	Typ.	Max.	Units
Ambient temperature		0		40 <sup>1,3</sup>	°C
Ambient humidity	Non-condensing	0		90	%Rh
Altitude / pressure <sup>2</sup>	Altitude (vs. sea level)	-0.1	0 ± 2.5	2	Km
	Ambient Pressure	0 <sup>2</sup>	0.75 ± 1	10.0	atm
Storage Conditions		Min.	Typ.	Max.	Units
Ambient temperature		-40		105	°C
Ambient humidity	Non-condensing	0		100	%Rh
Ambient Pressure		0		10.0	atm
ESD capability (Human body model)	Not powered; applies to any accessible part			±0.5	kV
	Original packaging			±15	kV
Mechanical Mounting		Min.	Typ.	Max.	Units
External heatsink (cooling plate)	Current capability depends on heat transfer, heatsink dimension, cooling technique (natural or forced). Keep lower plate temperature at maximum 75°C				
Environmental Characteristics		Min.	Typ.	Max.	Units
Size (Length x Width x Height)	Without mating connectors	104.2 x 90.5 x 46.8			mm
		~4.1 x 3.56 x 1.84			inch
Weight	Without mating connectors	300			g
Power dissipation	Idle (no load)	3			W
	Operating	80+100			W
Efficiency		98			%
Cleaning agents	Dry cleaning is recommended. Only Water- or Alcohol- based				
Protection degree	According to IEC60529, UL508	IP20			-
Logic Supply Input (+V <sub>LOG</sub> )		Min.	Typ.	Max.	Units
Supply voltage	Nominal values	12	24	36	V <sub>DC</sub>
	Absolute maximum values, drive operating but outside guaranteed parameters	8	24	40	V <sub>DC</sub>
	Absolute maximum values, surge (duration ≤ 10ms) <sup>†</sup>	-1		+45	V
Supply current	+V <sub>LOG</sub> = 12V		170		mA
	+V <sub>LOG</sub> = 24V		110		mA
	+V <sub>LOG</sub> = 36V		90		mA
Utilization Category	Acc. to 60947-4-1 (I <sub>PEAK</sub> ≤ 1.05 * I <sub>NOM</sub> )	DC-1			
Motor Supply Input (+V <sub>MOT</sub> )		Min.	Typ.	Max.	Units
Supply voltage	Nominal values	12	80	90	V <sub>DC</sub>
	Absolute maximum values, drive operating but outside guaranteed parameters	11		94	V <sub>DC</sub>
	Absolute maximum values, surge (duration ≤ 10ms) <sup>†</sup>	-1		95	V
Supply current	Idle		1	5	mA
	Operating	-130	±100	+130	A
	Absolute maximum value, short-circuit condition (Duration ≤ 10ms) <sup>†</sup>			140	A
Utilization Category	Acc. to 60947-4-1 (I <sub>PEAK</sub> ≤ 4 * I <sub>NOM</sub> )	DC-3			
Digital Inputs – opto-isolated- (IN0, IN1, IN2/LSP, IN3/LSN, IN4)		Min.	Typ.	Max.	Units
Mode compliance	PNP (J4, pin9 connected to GND)	Connect digital input pin to +V <sub>LOG</sub> to change its state			
	NPN (J4, pin9 connected to +V <sub>LOG</sub> )	Connect digital input pin to GND to change its state			
Default state	Input floating (wiring disconnected)	Logic LOW			
Input voltage	Logic LOW	0		5	V
	Logic HIGH	8		36	
	Absolute maximum	-5		50	
Input current	Logic LOW	0		14	mA
	Logic HIGH	0.6	4	6.6	
	Absolute maximum	0		7.5	
Input frequency			2		kHz
Minimum pulse			500		µs
ESD protection	Human body model	±15			kV

Motor Outputs (A/A+, B/A-, C/B+, BR/B-)		Min.	Typ.	Max.	Units
Nominal current *As long as drive lower plate does not exceed 75°C	PMSM motors sinusoidal amplitude			100	A
	PMSM motors sinusoidal RMS			71	A <sub>RMS</sub>
	DC/BLDC motors continuous			86.6	A
Peak current	*As long as drive back plate does not exceed 75°C	-130		+130	A
Short-circuit protection threshold				±140	A
Short-circuit protection delay		5	10		µs
On-state voltage drop	Nominal output current; including typical mating connector contact resistance		±0.3	±0.5	V
Off-state leakage current			±0.5	±1	mA
Motor inductance (phase-to-phase)	Recommended value, for current ripple max. ±5% of full range; +V <sub>MOT</sub> = 60 V	$F_{PWM}$ 20 kHz	300		µH
		40 kHz	150		
		60 kHz	100		
	Minimum value, limited by short-circuit protection; +V <sub>MOT</sub> = 60 V	20 kHz	150		µH
		40 kHz	75		
		60 kHz	50		
Motor electrical time-constant (L/R)	Recommended value for ±5% current measurement error	20 kHz	250		µs
		40 kHz	125		
		60 kHz	100		
		80 kHz	63		
Current measurement (FS = Full Scale accuracy)			±4	±8	%FS
Digital Outputs (OUT0/Brake, OUT1, OUT2, OUT3, OUT4)		Min.	Typ.	Max.	Units
Mode compliance		PNP 24V			
Default state	Not supplied (+V <sub>LOG</sub> floating or to GND)	High-Z (floating)			
Output voltage	Normal operation	Logic "High"			
	Logic "HIGH"; output current = 0.2A		V <sub>LOG</sub> -0.2	V <sub>LOG</sub> -0.8	V
	Logic "LOW"; output current = 0, no load	open-collector			
	Logic "HIGH", external load to GND	0			
	Absolute maximum, continuous	-0.3		V <sub>LOG</sub> +0.3	
Absolute maximum, surge (duration ≤ 1s) <sup>†</sup>	-0.5		V <sub>LOG</sub> +0.5		
Output current	Logic "HIGH", source current, continuous	OUT1,2,3,4	0.2		A
		OUT0/Brake	2		
	Logic "HIGH", source current, pulse ≤ 5 s	OUT1,2,3,4	0.4		A
		OUT0/Brake	3		
Logic "LOW", means High-Z					mA
Minimum pulse width		2			µs
ESD protection - Human body model		±15			kV
Mode compliance		NPN 24V			
Default state	Not supplied (+V <sub>LOG</sub> floating or to GND)	High-Z (floating)			
Output voltage	Normal operation	High-Z			
	Logic "LOW"; output current = 0.3A		0.2	0.8	V
	Logic "HIGH"; output current = 0, no load	open-collector			
	Logic "HIGH", external load to +V <sub>LOG</sub>		V <sub>LOG</sub>		
	Absolute maximum, continuous	-0.3		V <sub>LOG</sub> +0.3	
Absolute maximum, surge (duration ≤ 1s) <sup>†</sup>	-0.5		V <sub>LOG</sub> +0.5		
Output current	Logic "LOW", sink current, cont.	OUT1,2,3,4	0.3		A
		OUT0/Brake	2		
	Logic "LOW", sink current, pulse ≤ 5s	OUT1,2,3,4	0.5		A
		OUT0/Brake	3		
Logic "HIGH", means High-Z					mA
Minimum pulse width		2			µs
ESD protection - Human body model		±15			kV
Brake output (OUT0/Brake)		Min.	Typ.	Max.	Units
OUT0/Brake: solenoid driver, 2A.					
Default state	Not supplied (+V <sub>LOG</sub> floating or to GND)	High-Z (floating)			
	Immediately after power-up	Brake-	High-Z (floating)		
	Normal operation	Brake-	High-Z (floating)		
Output voltage	Logic "LOW" (Brake-)			0.2	V
	Logic "HIGH"; load present		+V <sub>LOG</sub>		
	Logic "HIGH", no load present		+5		
Absolute maximum, continuous		-0.5		+V <sub>LOG</sub> + 0.3	
Output current	Logic "LOW", sink current, continuous, Brake-			3	A
	Logic "HIGH", leakage current; external load to +V <sub>LOG</sub> ; V <sub>OUT</sub> = V <sub>LOG</sub> max = 36V			0.2	mA

<sup>1</sup> Operating temperature at higher temperatures is possible with reduced current and power ratings

<sup>2</sup> iGVD71 can be operated in vacuum (no altitude restriction), but at altitudes over 2,500m, current and power rating are reduced due to thermal dissipation efficiency.

Name ALN	First edition January 20, 2023	Document template: P099.TQT.564.0001	Last edition October 10, 2025	Visa: AS, GC
 <b>TECHNOSOFT</b>		<b>iGVD71 BX-CAT Intelligent Drive PRODUCT DATA SHEET</b>		N° document <b>P025.027.E221.DSH.011</b>
				Page: 3 of 4

# iGVD71 BX-CAT DATASHEET

P/N: P025.027.E221


Digital Hall Inputs (Hall1+, Hall1-, Hall2+, Hall2-, Hall3+, Hall3-) <sup>1</sup>		Min.	Typ.	Max.	Units	
Mode compliance		TTL / CMOS / Open-collector				
Default state	Input floating (Wiring disconnected)	Logic HIGH				
Input voltage	Logic "LOW"		0	0.8	V	
	Logic "HIGH"	2	5			
	Floating voltage (Not connected)	H1+, H2+, H3+		4.4		
		H1-, H2-, H3-		1.8		
Absolute maximum, surge (duration ≤ 1s) †	-10		+15			
Input current	Logic "LOW"; Pull to GND			1.2	mA	
	Logic "HIGH"; Internal 4.7kΩ pull-up to +5	0	0	0		
Minimum pulse width		2			μs	

Differential mode compliance		TIA/EIA-422-A			
Input voltage	Hysteresis	±0.06	±0.1	±0.2	V
	Differential mode	-14		+14	
	Common-mode range (A+ to GND, etc.)	-11		+14	
Input impedance, differential			120		Ω
Input frequency	Differential mode	0		10	MHz
Minimum pulse width	Differential mode	50			ns
ESD protection	Human body model	±5			kV

Encoder #1 and #2 Inputs (A1+, A1-, B1+, B1-, Z1+, Z1-, A2+, A2-, B2+, B2-, Z2+, Z2-) <sup>2</sup>		Min.	Typ.	Max.	Units
Differential mode compliance	For full RS422 compliance, see <sup>1</sup>	TIA/EIA-422-A			
Input voltage	Hysteresis	±0.06	±0.1	±0.2	V
	Differential mode	-14		+14	
	Common-mode range (A+ to GND, etc.)	-11		+14	
Input impedance, differential	A1+/A1-, B1+/B1-, Z1+/Z1-, A2+/A2-, B2+/B2-, Z2+/Z2-		120		Ω
Input frequency	Differential mode	0		10	MHz
Minimum pulse width	Differential mode	50			ns
Analog 0...5V Inputs (REF, FDBK)		Min.	Typ.	Max.	Units
Input voltage	Operational range	0		5	V
	Absolute maximum values, continuous	-12		+18	
	Absolute maximum, surge (duration ≤ 1s) †			±36	
Input impedance	To GND		18		kΩ
Resolution			12		bits
Integral linearity				±2	bits
Offset error			±2	±10	bits
Gain error			±1%	±3%	% FS <sup>3</sup>
Bandwidth (-3db)	Software selectable	0		1	kHz
ESD protection	Human body model	±5			kV

Safe Torque OFF (STO1+; STO1-; STO2+; STO2-)		Min.	Typ.	Max.	Units
Safety function	According to EN61800-5-2	STO (Safe Torque OFF)			
EN 61800-5-1/-2 and EN 61508-5-3/-4 Classification	Safety Integrity Level	safety integrity level 3 (SIL3)			
	PFFd (Probability of Failures per Hour - dangerous)	8*10 <sup>-10</sup>		hour <sup>1</sup> (0.8 FIT)	
EN13849-1 Classification	Performance Level	Cat3/PLe			
	MTTFd (meantime to dangerous failure)	377		years	
Mode compliance		PNP			
Default state	Input floating (wiring disconnected)	Logic LOW			
Input voltage	Logic "LOW" (PWM operation disabled)	-20		5.6	V
	Logic "HIGH" (PWM operation enabled)	18		36	
	Absolute maximum, continuous	-20		+40	
Input current	Logic "LOW"; pulled to GND		0		mA
	Logic "HIGH", pulled to +V <sub>LOG</sub>		5	10	
Diagnosis Pulse duration	Ignored high-low-high			5	ms
	Accepted pulse			20	Hz
PWM operation delay	From Enabled low-high transition to PWM operation enabled			30	ms
ESD protection	Human body model	±2			kV
EtherCAT®		Min.	Typ.	Max.	Units
Compliance		IEEE802.3, IEC61158			
Transmission line specification	According to TIA/EIA-568-5-A	Cat. 5e.UTP			
J7, J8 pinout	EtherCAT® supports MDI/MDI-X auto-crossover	TIA/EIA-568-A or TIA/EIA-568-B			
Software protocols compatibility		CoE, CiA402, IEC61800-7-301			
Node addressing <sup>*</sup>	By hardware sliding switch	1 + 31, 255			-
	By software	1 + 255			
MAC addressing		none			
ESD protection	Human body model	±15			kV
Remark: When Axis ID is 255, the EtherCAT register called "configured station alias" will be 0.					
Supply Output (+5V)		Min.	Typ.	Max.	Units
Output voltage	Current sourced = 250mA	4.8	5	5.2	V
Output current		600	650		mA
Short-circuit		Protected			
Over-voltage		NOT protected			
ESD protection	Human body model	±1			kV
Conformity		Min.	Typ.	Max.	Units
EU Declaration - Pending-	2014/30/EU (EMC), 2014/35/EU (LVD), 2011/65/EU (RoHS), 1907/2006/EC (REACH), 93/68/EEC (CE Marking Directive), EC 428/2009 (non dual-use item, output frequency limited to 590Hz)				

† Stresses beyond values listed under "absolute maximum ratings" may cause permanent damage to the device. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.



<sup>1</sup> Differential input pins have internal 120Ω termination resistors connected across when SW1 pins 8, 9 are ON  
<sup>2</sup> All differential input pins can have internal 120Ω termination resistors connected across (see SW1 settings)

<sup>3</sup> "FS" stands for "Full Scale"

Name ALN	First edition January 20, 2023	Document template: P099.TQT.564.0001	Last edition October 10, 2025	Visa: AS, GC
		Title of document <b>iGVD71 BX-CAT Intelligent Drive PRODUCT DATA SHEET</b>	N° document <b>P025.027.E221.DSH.011</b>	
		Page: 4 of 4		