



All dimensions are in mm. Drawings not to scale.

Sensor \ Motor	PMSM	BLDC	DC BRUSH	STEP (2-ph)	STEP (3-ph)
Incr. Encoder	●			●	●
Incr. Encoder + Hall	●	●			
Analog Sin/Cos encoder	●	●	●	●	
SSI	●	●	●	●	
BiSS-C	●	●	●	●	
Tacho			●		
Open-loop (no sensor)				●	●

Features

- Motion controller and drive in a single compact unit based on MotionChip™ technology
- Universal solution for control of rotary and linear brushless, brushed and 2 or 3-phase step motors
- Advanced motion control capabilities (PVT, S-curve, electronic cam)
- Motor supply: 11-80V; Logic SELV/PELV supply: 9-36V; STO SELV/PELV supply: 18-40V
- Output current: 20A cont. (BLDC mode); 40A_{PEAK}, up to 60kHz PWM
- Feedback Devices (dual-loop support)
 - 1st feedback devices supported:
 - Incremental encoder interface (differential)
 - Analogue sin/cos encoder interface (differential 1V_{pp})
 - Digital Hall sensor interface (single-ended and open collector)

2nd feedback devices supported:

- Incremental encoder interface (differential)
- BiSS / SSI encoder interface
- pulse & direction interface (differential) for external (master) digital reference
- STO: 2 safe torque-off inputs, safety integrity level (SIL3/Cat3/PLe) acc. to EN61800-5-1; -2/ EN61508-3; -4/ EN ISO 13849-1.
- 4 digital inputs, 12-36V, PNP/NPN programmable: 2 for limit switches, 2 general-purpose
- 4 digital outputs, 5-36V, NPN open-collector: Ready, Error, OUT1 0.5A and OUT0 2A
- 2 analogue inputs: 12 bit, +/-10V and 0-5V: Reference and Feedback (for Tacho) or general purpose
- RS-232 serial & dual RJ45 CAN connectors
- TMLCAN and CANopen (CiA 301 v4.2, CiA 305 v.2.2.13 and CiA 402 v3.0) protocols selectable by DIN switch
- 127 h/w addresses selectable by DIN switch
- 16k x 16 SRAM memory for data acquisition
- 16k x 16 E²ROM memory to store setup data, TML motion programs, cam tables and other user data
- Operating ambient temperature: 0-40°C (over 40°C with derating)
- NTC/PTC analogue Motor Temperature sensor input
- Protections: short-circuit between motor phases and from motor phases to GND, over/under-voltage, over-current, I²t, control error, over temperature, communication error

Name EP	First edition December 12, 2019	Document template: P099.TQT.564.0001	Last edition December 12, 2019	Visa : AN
 TECHNOSOFT	Title of document iPOS8020 BX-CAN PRODUCT DATA SHEET	N° document P029.026.E201.DSH.10G	Page: 1 of 5	

